

## Specifications

	KC-550	KC-350	KC-150	KC-60	KCW-1
Rated Power Output	180 W	120 W	65 W	40 W	200W
Nominal Input Level (1 kHz)	CH 1 (MIC/LINE)	-50 to -20 dBu	-50 to -20 dBu	-50 to -20 dBu	-50 to -20 dBu
	CH 2-4 (LINE)	-20 dBu	-20 dBu	-20 dBu	-20 dBu
	STEREO LINK	0 dBu	0 dBu	—	—
	AUX	-10 dBu	-10 dBu	-10 dBu	-10 dBu
Nominal Output Level (1 kHz)	LINE OUT	+4 dBu	+4 dBu	+4 dBu	+4 dBu
	STEREO LINK	0 dBu	0 dBu	—	—
	SUB WOOFER	+4 dBu	+4 dBu	+4 dBu	+4 dBu
Speakers	38 cm (15 inches) x 1, Tweeter x 1	30 cm (12 inches) x 1, Tweeter x 1	30 cm (12 inches) x 1, Tweeter x 1	25 cm (10 inches) x 1, Tweeter x 1	25 cm (10 inches) x 1
Connectors	CH1 INPUT Jack (XLR type) CH1-4 INPUT L (MONO) Jacks (1/4" phone type) CH1-4 INPUT R Jacks (1/4" phone type) LINE OUT L (MONO) Jacks (XLR type, 1/4" phone type) LINE OUT R Jacks (XLR type, 1/4" phone type) AUX IN Jacks (RCA phono type) SUBWOOFER OUT Jack (1/4" phone type) STEREO LINK OUT Jack (1/4" phone type) STEREO LINK IN Jack (1/4" phone type) PHONES Jack (Stereo 1/4" phone type)	CH1 INPUT Jack (XLR type) CH1-4 INPUT L (MONO) Jacks (1/4" phone type) CH1-4 INPUT R Jacks (1/4" phone type) LINE OUT L (MONO) Jack (1/4" phone type) LINE OUT R Jack (1/4" phone type) AUX IN Jacks (RCA phono type) SUBWOOFER OUT Jack (1/4" phone type) STEREO LINK OUT Jack (1/4" phone type) STEREO LINK IN Jack (1/4" phone type) PHONES Jack (Stereo 1/4" phone type)	Channel 1 Input Jacks (XLR type, 1/4" phone type) Channel 2 Input Jack (1/4" phone type) Channel 3 Input Jack (1/4" phone type) Channel 4 Input Jack (1/4" phone type) AUX IN Jacks (RCA phono type) LINE OUT Jack (1/4" phone type) SUB WOOFER OUT Jack (1/4" phone type) PHONES Jack (1/4" TRS phone type, mono signal output)	Channel 1 Input Jacks (XLR type, 1/4" phone type) Channel 2 Input Jack (1/4" phone type) Channel 3 Input Jack (1/4" phone type) AUX IN Jacks (RCA phono type) LINE OUT Jack (1/4" phone type) SUB WOOFER OUT Jack (1/4" phone type) PHONES Jack (1/4" TRS phone type, mono signal output)	INPUT Connectors L, R (XLR type) INPUT Jacks L (MONO), R (1/4" phone type) THRU OUT Connectors L, R (XLR type) THRU OUT Jacks L, R (1/4" phone type) FOOT SW Jack (SUBWOOFER ON/OFF)
Power Supply	AC 117 V, AC 230 V, AC 240 V	AC 117 V, AC 230 V, AC 240 V	AC 117 V, AC 230 V, AC 240 V	AC 117 V, AC 230 V, AC 240 V	AC 117 V, AC 230 V, AC 240 V
Power Consumption	135 W	100 W	55 W	45 W	135 W
Dimensions	590 (W) x 445 (D) x 536 (H) mm, 23-1/4 (W) x 17-9/16 (D) x 21-1/8 (H) inches (excluding casters)	490 (W) x 385 (D) x 470 (H) mm, 19-5/16 (W) x 15-3/16 (D) x 18-9/16 (H) inches	480 (W) x 295 (D) x 435 (H) mm, 18-15/16 (W) x 11-5/8 (D) x 17-1/8 (H) inches	420 (W) x 300 (D) x 410 (H) mm, 16-9/16 (W) x 11-13/16 (D) x 16-3/16 (H) inches	438 (W) x 440 (D) x 460 (H) mm, 17-1/4 (W) x 17-3/8 (D) x 18-1/8 (H) inches
Weight	29.0 kg, 63 lbs 15 oz	22.0 kg, 48 lbs 9 oz	14.0 kg, 30 lbs 14 oz	12.5 kg, 27 lbs 9 oz	23.0 kg, 50 lbs 12 oz
Accessories	Owner's Manual, Casters (x4)	Owner's Manual	Owner's Manual	Owner's Manual	Owner's Manual, Power Cord

\* 0 dBu = 0.775 Vrms

# Roland®

# KC Keyboard Amplifier

## Simply the Best



## The Ultimate Amplifier for Keyboards and Organ.

The KC-1000 is our most powerful keyboard amp ever. This 5-channel tower uses DSP technology and a 310-watt/7-speaker system to accurately reproduce the full frequency range of organs, synthesizers and other electronic musical instruments. Onboard RSS® and COSM® effects create realistic tone cabinet reverberation when used with VK-Series organs, while unique ambient effects, split-frequency compression and 3-band EQ make the KC-1000 perfect for performance.

### Specifications

- **Rated Power Output** 310W
- **Speakers** 15" (38 cm) x 1, 6.3" (16 cm) x 4, 1" (2.5 cm) x 2
- **Controls** Channel Organ Volume, Cabinet Modeling Sound Type, Orchestral Volume, Synth/AUX Volume, Mic Volume, Ambience Volume, Tone Control Low, Tone Control Middle, Tone Control High, Master Volume, Line Out Volume, Phones Volume
- **Connectors** ORGAN Input (L/Mono, R), ORCHESTRAL Input (L/Mono, R), SYNTH/AUX Input (L/Mono, R), MIC Input (Mono), STEREO LINK OUT, STEREO LINK IN, LINE OUT (XLR type balanced L, R, 1/4" phone type unbalanced L/Mono, R), HEADPHONES
- **Power Consumption** 225W (AC 117/230/240 V)
- **Dimensions** (incl. the casters) 595 (W) x 535 (D) x 970 (H) mm (23-7/16" x 21-1/16" x 38-3/16")
- **Weight** 64 kg (141 lbs. 2 oz.)



**KC-1000**  
Stereo Mixing Keyboard Amplifier

## Options



**DR-20**  
Dynamic microphone



**RH-50**  
Headphones



**DP-2**  
Pedal Switch



**FS-5U**  
Footswitch

**Roland®**  
WE DESIGN THE FUTURE

Visit us online at [www.roland.co.jp](http://www.roland.co.jp)

All specifications and appearances are subject to change.  
All trademarks are the property of their respective companies.

Printed in Japan September 2002 RAM-3612 ERK-NK ADE-2

# A Tradition of Quality and Convenience

## Now More Powerful Than Ever!

The Roland KC-Series is the world's most popular line of keyboard amplifiers. And now, there's even more to brag about. All models feature multiple input channels, a stereo Auxiliary input and Microphone input, plus subwoofer compatibility and clean sound ideal for electronic musical instruments.



### KC-550 4-CH Stereo Mixing Keyboard Amplifier



Control Panel



Rear Panel

- Flagship keyboard amplifier with powerful 180-watt/15" speaker and horn tweeter
- Accommodates up to 4 stereo inputs, plus stereo Aux input and XLR Mic input
- Output Select feature and convenient Shape switch for tonal adjustment
- 3-band EQ and Subwoofer output compatible with new KCW-1
- Stereo Link feature, plus XLR Line output for connection to mixing consoles

### KC-350 4-CH Stereo Mixing Keyboard Amplifier



Control Panel



Rear Panel

- Stereo mixing keyboard amplifier with 120-watt/12" speaker and horn tweeter
- Accommodates up to 4 stereo inputs, plus stereo Aux input and XLR Mic input
- Output Select feature and convenient Shape switch for tonal adjustment
- 3-band EQ and Subwoofer output compatible with new KCW-1
- Stereo Link feature, plus 1/4" output for connection to recording devices

### KC-150 4-Channel Mixing Keyboard Amplifier



Control Panel



Rear Panel

- Compact keyboard amplifier with 65-watt/12" speaker and piezo tweeter
- Accommodates up to 4 mono inputs, plus stereo Aux input and XLR Mic input
- 2-band EQ and Subwoofer output compatible with new KCW-1
- Headphones output and mono Line output

### KC-60 3-Channel Mixing Keyboard Amplifier



Control Panel



Rear Panel

- Affordable keyboard amplifier with 40-watt/10" speaker and piezo tweeter
- 3-channel design includes 1/4" Line input and XLR Microphone input
- 2-band EQ and Subwoofer output compatible with new KCW-1
- Stereo Auxiliary input (RCA type), Headphones output and mono Line output


### KCW-1 Powered Subwoofer



Control Panel


- 200-watt powered subwoofer for use with Roland's KC-Series amps
- Stereo Thru Out jack (XLR and 1/4") for amps without a Subwoofer output
- Intuitive controls including Crossover knob, Phase switch and Bottom switch
- Footswitch jack for muting the subwoofer output.

## When choosing a keyboard amplifier, make sure it measures up to this:




### Up to 4-Channel Mixing

All KC amplifiers feature a flexible mixing section designed with the performing musician in mind. Our flagship models feature up to four stereo inputs, and all KC amps include a Microphone input and stereo Auxiliary input for connecting CD players.



### Stereo Link Capabilities

The KC-350 and KC-550 include Roland's Stereo Link feature for chaining two amplifiers. Using a single cable, you can connect two KC amps for true stereo sound while controlling them both from the amp nearest you on stage.



### Subwoofer-Ready

Want more low end? Simply add an optional subwoofer like Roland's new KCW-1. Connections are easy, thanks to the Subwoofer output found on all new KC amps. Now even the most affordable models can sound huge!



### Made for the Road

KC amps are built for life on the road. All models have built-in handles for easier transportation (the KC-550 also includes casters) and a rugged design with heavy-duty carpeting, protective edges and an all-metal grille.